

## 10        **WIDEBAND COMMUNICATION USING DELAY LINE CLOCK MULTIPLIER**

             This patent application claims the priority of U.S. Provisional Patent Application No. 60/198,147, the entirety of which is incorporated herein by reference.

15

### FIELD OF THE INVENTION

20

             The present invention relates generally to the field of data communications. Specifically, the present invention relates to a data sampling system which may be used in for example synchronization procedures such as those used in wideband spread spectrum communication.

### BACKGROUND OF THE INVENTION

25

             Spread spectrum communication is a type of signal modulation in which a signal to be transmitted is spread over a bandwidth that substantially exceeds the data transfer rate or the minimum bandwidth required to transmit the signal. Fundamentally, in channels with narrowband noise, increasing the transmitted signal bandwidth decreases the interference effect of such noise since the signal instead of being concentrated in a particular band is now spread out over a much wider band.

Signal spreading may be achieved using any of a number of different techniques, including direct sequence, frequency hopping or a hybrid combination. In direct sequence spread spectrum, a periodic, relatively high frequency, repetitive pseudo-noise code (PN) is mixed with the data signal using XOR gates or a mixer, and the resulting signal is then modulated using, e.g., binary phase shift keying (BPSK) or quadrature phase shift keying (QPSK). This process causes the transmitted signal to be replaced by a very wide bandwidth signal with the spectral equivalent of a noise signal. At the receiver, the demodulation process involves the mixing and multiplying of the same PN code with the received signal. This produces a correlated signal which is maximum when the PN code matches the received signal. The correlated signal is then filtered and demodulated.

In frequency hopping spread spectrum, the signal stream to be transmitted is shifted in frequency by an amount determined by a code that spreads the signal power over a wide bandwidth. This is accomplished using a PN code controlled frequency synthesizer. In this way, the instantaneous frequency output of the transmitter jumps from one value to another based on the PN code. By changing the instantaneous frequency of the output signal, the output frequency spectrum is effectively spread over the range of the wider bandwidth.

The PN codes used in direct sequence spread spectrum systems consist of individual units called "chips" which can have two values, either -1/1 in a polar system or 0/1 in a binary system. In general, these PN codes must have a sharp (e.g., one chip wide) autocorrelation peak to allow for proper code synchronization, as well as a low cross-correlation value to allow for more users in the system. Additionally, the codes should be balanced, i.e., the number of ones and zeros may only differ by a maximum of one. This latter requirement allows for good spectral density such that the signal energy may be uniformly spread over the entire frequency band. Codes which may be used in direct sequence spread spectrum systems include Walsh-Hadamard codes, M-sequences, Gold codes and Kasami codes. These codes may be either orthogonal or non-orthogonal.

One difficulty encountered in spread spectrum systems is achieving proper synchronization, i.e., having the receiver lock onto and synchronize with the bit timing of the transmitter so that the receiver is sampling and segmenting the received signal at the proper bit boundaries intended by the transmitter. One approach to achieving synchronization is disclosed in U.S. Patent No. 5,727,004 entitled METHOD AND APPARATUS FOR DATA ENCODING AND COMMUNICATION OVER NOISY MEDIA, and assigned to the assignee of the present application, the contents of which are incorporated herein by reference. The synchronization procedure disclosed in U.S. Patent No. 5,727,004 oversamples the received signal at a number of points which are offset in time by a fraction of the bit interval (i.e., sub-interval). Each of the sampled signals is analyzed to determine which of the bit intervals results in good correlation and therefore represents the proper bit boundaries. The oversampling of the incoming signal at a number of sub-intervals generally requires either a clock or some other timing source running at a multiple of the bit clock in order to sample the signal at sub-interval increments.

The FCC regulations governing electromagnetic radiation limits, 47 CFR § 15.107, 109, 209, ..... place limits on radiated and conducted emissions for both intended and unintended emissions. The term "intended" refers to the intended mode of transmission. For example, in the case of wireless communication, the "intended" mode of transmission is radiated, while the unintended mode of transmission is conducted. Similarly, in the case of wired communication, the "intended" mode of transmission is conducted, while the unintended mode of transmission is radiated.

## SUMMARY OF THE INVENTION

The present invention is directed to a delay line clock multiplier for use in a communication system, such as a spread spectrum system, in which a delay line is used as a clock multiplier for generating a higher speed clock that may be

used, for example, for data sampling. The speed and timing characteristics of the clock delay line are adjusted by controlling the supply voltage to the delay line. Additionally, by utilizing the spread spectrum approach, the electromagnetic emissions can be kept below the FCC imposed limits. Generally, as a signal is spread over a wider spectrum utilizing higher frequencies there results a problem in achieving proper synchronization at those higher frequencies. However, utilizing the present invention, a signal may be spread over a wide frequency band because proper synchronization may be achieved at the higher frequencies using an oversampling synchronization approach which in turn is made possible by the delay line clock multiplier which allows for the oversampling of a signal at sub-interval increments.

According to the present invention, a multiple stage delay line is used as a clock multiplier for generating a high speed clock signal from a relatively low speed clock source. The delay line includes an odd number of delay stages and the output of the last delay stage is connected to the input of the first delay stage in essentially an oscillator or inverter ring configuration. Normally, an inverter ring contains alternating 1s and 0s in the successive stages of the ring. However, the inverter ring of the present invention is perturbed or initialized to contain the same value in two successive stages (e.g. two 1s or two 0s in a row) in order to create a distinctive transition or edge pattern which cycles through the ring.

The contents of the delay line, i.e., the state of the delay line at a particular stage, which is essentially a square wave with alternating 1s and 0s is input to a phase comparator. The other input to the phase comparator is connected to the slow speed clock signal. The output of the phase comparator is an indication of the relative speeds of the two input signals, viz., the slow speed clock and the delay line contents, and is used to control a voltage adjustment circuit which in turn adjusts one or both of the supply voltages to the delay line to thereby adjust the switching speed of the individual gates or stages that make up the delay line.

Essentially, the phase comparator and voltage adjustment circuit act to speed up or slow down the delay line to match the slow speed clock signal. If the delay line is running too slow, the supply voltages are adjusted to decrease the voltage difference between them. As a result, the individual gates of the delay line switch a smaller voltage difference in going from high to low (or low to high) and are thus able to switch faster. Conversely, if the delay line is running too fast, the supply voltages are increased so as to increase the voltage difference between them. This slows down the individual gate elements which must now switch a larger voltage difference for each high to low (or low to high) transition. It should be noted that when the delay line and the slow speed clock are properly matched, the speed of the delay line (i.e., the delay through all the stages of the delay line) is actually twice that of the slow speed clock, since each stage in the delay line must include two periods (high and low) to match the square wave slow speed clock signal. The delay through all the stages of the delay line corresponds to one phase of the slow speed clock signal so the delay through the delay line is less than the period of the slow speed clock signal.

Once the clock delay line is running at the appropriate speed, this in turn establishes the corresponding control voltages which result in that speed. The control voltages are also applied to another delay line (series connected inverters) which is essentially used as a serial shift register causing it in turn to run at the same speed as the first delay line. The input to the second delay line is the serial stream of incoming data, and the individual stages of the second delay line act to oversample the incoming data at a number of successive subintervals. Each of the subinterval samples is latched for subsequent processing and compensated for the inversion of the individual stages introduced by the inverter. In this way, adjusting the control voltage acts to adjust the timing of the delay lines in order to oversample the incoming data signal in order to achieve proper synchronization.

#### BRIEF DESCRIPTION OF THE DRAWINGS

Other objects, features and advantages of the invention discussed in the above brief explanation will be more clearly understood when taken together with the following detailed description of an embodiment which will be understood as being illustrative only, and the accompanying drawings reflecting aspects of that embodiment, in which:

Figure 1 is a block diagram of a delay line clock multiplier oversampling circuit according to the present invention;

Figure 2 is a schematic diagram of a delay line configured as a sampling shift register;

Figure 3 is a schematic diagram of a delay line configured as an oscillator;

Figure 4 is a schematic diagram of an inverter stage; and

Figure 5 is an illustration of the voltage transfer characteristics of an inverter stage.

#### DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Referring now to Figure 1, therein is shown a block diagram of a delay line clock multiplier oversampling circuit 10 according to the present invention. The clock multiplier circuit 10 includes a clock source 100 which is also referred to herein as a slow speed clock source since the clock and timing signals generated by the clock multiplier circuit 10 result in a faster speed clock signal than that of clock source 100. In the specific example illustrated in Figure 1 and described herein, clock source 100 is a 14 MHZ clock; however, it should be understood that the speed of clock source may of course be varied to other frequencies depending on the particular application.

The output of clock source 100 is applied as an input to phase comparator 102. The other input to phase comparator 102 is connected to the output stage 104 of a delay line 106. The operation of delay line 106 will be described in greater detail below. The function of phase comparator 102 is to

produce an output signal on line 108 which is an indication of the relative speeds or phases of the two input signals to the phase comparator 102. The phase comparator output signal is provided to a control voltage adjustment circuit 110 that, depending on the output signal from the phase comparator 102, adjusts the power supply or reference voltages applied to delay line 106.

Essentially, control voltage adjustment circuit 110 is responsive to the output signal from the phase comparator 102 to either increase or decrease one or more of the power supply voltages supplied to the delay line 106 in order to slow down or speed up the switching operation of delay line 106. As shown in Figure 3, in one illustrative embodiment the delay line 106 consists of a number of series connected inverters I'1, I'2, . . . followed by a buffer B. Thus, the delay line functions as an oscillator. In the specific embodiment illustrated in Figure 3, delay line 106 includes 31 inverter stages followed by the buffer B. Further, the output of the buffer B is connected to the input of the first inverter I'1 in order to provide an inverter ring or oscillator. Each of the inverters in delay line 106 is constructed generally according to the circuit diagram of Figure 4. As shown in Figure 4, each inverter stage includes a P-channel transistor 402 connected to an N-channel transistor 404. The gate inputs to the transistors 402 and 404 are connected together and act as the input node  $V_{IN}$ , while the drains of the two transistors are likewise connected together and act as the output node  $V_{OUT}$ .

The circuit configuration of Figure 4 acts as an inverter, i.e., a logic high input (1) results in a logic low output (0) and vice versa. The voltage transfer characteristics of the circuit of Figure 4 are illustrated in Figure 5 as a function of supply voltage  $V_{CC}$ . As shown in Figure 5, as the supply voltage  $V_{CC}$  decreases, the switching speed of the inverter increases since the voltage swing between the logic levels decreases. The control voltage adjustment circuit 110 acts to adjust the supply voltage  $V_{CC}$  in order to adjust the switching speed of the individual inverter stages of delay line 106. The circuits such as are shown in Figure 4 have two supply voltages  $V_{CC}$  and GND, with the effective voltage supplied to the circuit

being the differential voltage between the two supplies, i.e.,  $V_{CC} - GND$ . The object of control voltage adjustment circuit 110 is to adjust this differential voltage, which of course may be achieved by modifying one or both of  $V_{CC}$  and GND.

Phase comparator 102 and control voltage adjustment circuit 110  
 5 operate to adjust the supply voltage  $V_{CC}$  and, thus, the speed of delay line 106 so that the delay time through the 32 stages (31 inverters I'N and buffer B) of delay line 106 is the same as the slow speed clock signal generated by the clock 100.

The adjusted supply voltage  $V_{CC}$  from the control voltage adjustment circuit 110 is also applied to a second delay line 112 (FIGS. 1 and 2). In the  
 10 illustrative embodiment of FIGS. 1 and 2, the second delay line 112 includes thirty one (31) series-connected inverters I1 through I31. The input of the first inverter I1 is connected to the incoming signal line 114 that transmits the serial data being received. A plurality of output lines  $D_0$  through  $D_{31}$  are connected to the second delay line 112 and to a latch 116. The line  $D_0$  is connected to the input of inverter  
 15 I1, while the lines  $D_1$  through  $D_{31}$  are connected to the outputs of the respective inverters I1 through I31.

The latch 116 is triggered by the output from the delay line 106. In the illustrative embodiment, because the clock source 100 operates at 14 MHZ, the output from the delay line serves as a 28 MHZ clock. Thus, the latch operates at  
 20 the increased frequency, such that the serial data is oversampled. Each bit is sampled 32 times.

Thus, by adjusting the phase of the delay line 106 through the control voltage adjustment circuit 110, the circuit 10 of the present invention is controlled to oversample the serial data signal in order to achieve proper synchronization.

25 From the foregoing, it will be apparent that the system 10 of the present invention serves to oversample an incoming serial data stream in order to achieve proper synchronization between the receiver and transmitter.



While a form of the invention has been illustrated and described, it will be apparent to those skilled in the art that various modifications and improvements may be made without departing from the spirit and scope of the invention.

100 101 102 103 104 105 106 107 108 109 110 111 112 113 114 115 116 117 118 119 120 121 122 123 124 125 126 127 128 129 130 131 132 133 134 135 136 137 138 139 140 141 142 143 144 145 146 147 148 149 150 151 152 153 154 155 156 157 158 159 160 161 162 163 164 165 166 167 168 169 170 171 172 173 174 175 176 177 178 179 180 181 182 183 184 185 186 187 188 189 190 191 192 193 194 195 196 197 198 199 200 201 202 203 204 205 206 207 208 209 210 211 212 213 214 215 216 217 218 219 220 221 222 223 224 225 226 227 228 229 230 231 232 233 234 235 236 237 238 239 240 241 242 243 244 245 246 247 248 249 250 251 252 253 254 255 256 257 258 259 260 261 262 263 264 265 266 267 268 269 270 271 272 273 274 275 276 277 278 279 280 281 282 283 284 285 286 287 288 289 290 291 292 293 294 295 296 297 298 299 300 301 302 303 304 305 306 307 308 309 310 311 312 313 314 315 316 317 318 319 320 321 322 323 324 325 326 327 328 329 330 331 332 333 334 335 336 337 338 339 340 341 342 343 344 345 346 347 348 349 350 351 352 353 354 355 356 357 358 359 360 361 362 363 364 365 366 367 368 369 370 371 372 373 374 375 376 377 378 379 380 381 382 383 384 385 386 387 388 389 390 391 392 393 394 395 396 397 398 399 400 401 402 403 404 405 406 407 408 409 410 411 412 413 414 415 416 417 418 419 420 421 422 423 424 425 426 427 428 429 430 431 432 433 434 435 436 437 438 439 440 441 442 443 444 445 446 447 448 449 450 451 452 453 454 455 456 457 458 459 460 461 462 463 464 465 466 467 468 469 470 471 472 473 474 475 476 477 478 479 480 481 482 483 484 485 486 487 488 489 490 491 492 493 494 495 496 497 498 499 500 501 502 503 504 505 506 507 508 509 510 511 512 513 514 515 516 517 518 519 520 521 522 523 524 525 526 527 528 529 530 531 532 533 534 535 536 537 538 539 540 541 542 543 544 545 546 547 548 549 550 551 552 553 554 555 556 557 558 559 560 561 562 563 564 565 566 567 568 569 570 571 572 573 574 575 576 577 578 579 580 581 582 583 584 585 586 587 588 589 590 591 592 593 594 595 596 597 598 599 600 601 602 603 604 605 606 607 608 609 610 611 612 613 614 615 616 617 618 619 620 621 622 623 624 625 626 627 628 629 630 631 632 633 634 635 636 637 638 639 640 641 642 643 644 645 646 647 648 649 650 651 652 653 654 655 656 657 658 659 660 661 662 663 664 665 666 667 668 669 670 671 672 673 674 675 676 677 678 679 680 681 682 683 684 685 686 687 688 689 690 691 692 693 694 695 696 697 698 699 700 701 702 703 704 705 706 707 708 709 710 711 712 713 714 715 716 717 718 719 720 721 722 723 724 725 726 727 728 729 730 731 732 733 734 735 736 737 738 739 740 741 742 743 744 745 746 747 748 749 750 751 752 753 754 755 756 757 758 759 760 761 762 763 764 765 766 767 768 769 770 771 772 773 774 775 776 777 778 779 780 781 782 783 784 785 786 787 788 789 790 791 792 793 794 795 796 797 798 799 800 801 802 803 804 805 806 807 808 809 810 811 812 813 814 815 816 817 818 819 820 821 822 823 824 825 826 827 828 829 830 831 832 833 834 835 836 837 838 839 840 841 842 843 844 845 846 847 848 849 850 851 852 853 854 855 856 857 858 859 860 861 862 863 864 865 866 867 868 869 870 871 872 873 874 875 876 877 878 879 880 881 882 883 884 885 886 887 888 889 890 891 892 893 894 895 896 897 898 899 900 901 902 903 904 905 906 907 908 909 910 911 912 913 914 915 916 917 918 919 920 921 922 923 924 925 926 927 928 929 930 931 932 933 934 935 936 937 938 939 940 941 942 943 944 945 946 947 948 949 950 951 952 953 954 955 956 957 958 959 960 961 962 963 964 965 966 967 968 969 970 971 972 973 974 975 976 977 978 979 980 981 982 983 984 985 986 987 988 989 990 991 992 993 994 995 996 997 998 999 1000